

| BLANK B.O.Q OF ELECTRICAL WORK FOR BARODA UP BANK AT MANSURGANJ BRANCH | | | | |
|--|---|------|-----|------|
| B | SCHEDULE - 'B' (ELECTRICAL WORK) | | | |
| SL No | PARTICULARS | UNIT | QTY | RATE |
| 1 | ELECTRICAL WIRING & EARTHING | | | |
| 1.1 | Supply, laying, connection & testing of light, fan point, wiring by 2x1.5mmsq(2x3/.029) + 1x1mmsq PVC insulated, multistrand single core copper conductor FRLS wire maintaining the colour code as per direction in PVC conduit of 20mm with ISI mark 1.5mm thickness to conceal in wall partition mending good the damage, complete with PVC circular box, bend to be done as per drawing including 3 point ceiling rows wherever required GI saddle to be used for fixing, metal flexible/PVC flexible pipe may use if required in partition wall. All PVC pipes should be with ISI mark. No joints will be allowed inside pipe, light, fan & plug point complete with modular type switch plate & MS box. rate Including the main circuit line 2x2.5mmsq+1x1.5mmsq earth PVC insulated Cu. Wire from DB to switch board, maintaining the colour code. Circuit line for lighting switch board & 6Amps plug board are to be drawn from lighting DB to Lighting board & plug point board (independent), 6/16 Amps plug point line are to be drawn from power DB as per DB schedule /SLD | | | |
| a) | 1 light by 1 switch | Nos. | 25 | |
| e) | Ceiling fan point with step type electronic regulator | No | 9 | |
| f) | Same as above, but for exhaust fan excluding regulator. | No | 3 | |
| g) | Same as above 5A Point in the switchboard itself. | No | 8 | |
| h) | same as above Wiring for call-bell point including buzzer | No | 1 | |
| i) | Wiring (2x2.5mmsq+1x1.5mmsq from power DBs) for independent 6A multi pin socket at walls along with 6A modular type switches board housed in painted MS box (upto 3 independent plug points can be taken in one circuit). For wall Fan | No | 1 | |
| 1.2 | Supply and installation of modular type 2 nos 6A & multi pin sockets with 2 nos 6 Amp one way switch housed in MS box to be fixed in partitions or concealed in wall. The box shall be painted with 2 coats of enamel paint over a coat of red oxide primer including wiring for Raw power socket outlet using 2 R runs of 2.50 sqmm and single run of 1.5 sqmm PVC insulated multi stranded single core copper conductor FRLS wire in 20mm PVC conduit to be laid in floor, partitions, etc. complete with all accessories (looping 2 sets of 2x6A socket outlet in one circuit- from DB) (Raw power). for counter (Each counter 1 Nos +BM :2 Nos, ATM 1No., Pantry 1No.:) | No | 5 | |
| 1.3 | Supply and installation modular type 16A, 5-pin socket with 16A one way switch housed in MS box to be fixed in partitions or concealed in wall. The box shall be painted with 2 coats of enamel paint over a coat of red oxide primer, the rate shall include wiring fusing 2R 4.0 sqmm & single run of 2.5 sqmm PVC insulated multi stranded single core copper conductor FRLS wire in 25mm PVC conduit to be laid in floor, partitions, etc complete with all accessories (for line printer : or optional).(upto 2 independent plug points can be taken in one circuit) C.C :1No. BM.;1 No.: Alternative counter 2No + Banking Hall 1 No+ Pantry 1No, ATM :1No) | Nos. | 5 | |
| 3 | AC POINTS | | | |
| 3(a) | Same as serial no.1, but wiring for A/C socket by using 2*4 sq.mm. PVC insulated 1100 V grade copper conductor wire and earthing with 1*4.0 sq.mm. PVC insulated 1100 V grade copper conductor wire with modular type AC box (tiny trip type) with socket complete in all respects controlled by 25/32 A SP MCB to be provided near indoor unit | Nos. | 4 | |

| | | | | | |
|------------|---|------|----|--|--|
| 2 | LAYING OF CABLE : | | | | |
| 2.1 | Supply laying fixing main power with 50mm sq 3.5 core PVC insulated,PVC sheated Alu.Conductor, 1100 v. grade armoured cable complete with 02 nos 8 SWG bear GI.wire as running earth .(Meter panel to Main Panel & Dgset to Main Panel) | Mts. | 0 | | |
| 2.2 | End termination of 50mmsq 3.5 Core armoured cable,complete with brass cable gland , Alu. Lug, PVC tape. | Nos | 0 | | |
| 2.3 | - Do - 3.5 x 16 sqmm with 02 nos 8 SWG bear GI.wire as running earth. for Light D.B | Mts | 20 | | |
| 2.4 | - Do - 3.5 x 25 sqmmth with 02 nos 8 SWG bear GI.wire as running earth. for POWER & A.C D.B , UPS & ATM | Mts | 20 | | |
| 2.5 | - Do - termination of 25 & 16 Sqmm 3.5 Core | Nos | 8 | | |
| 3 | Out door type glow sign board wiring :- | | | | |
| 3.1 | Supply laying of main line with 2x2.5 +1x1.5 mmsq through MS conduite from main panal to glow sign board. | Mts | 20 | | |
| 3.2 | Supply installation of 16 amps DP MCB at main entrance Glow sign board & With Electronic timer as required. | Set | 1 | | |

| | | | | | |
|-------------|--|-----|----|--|--|
| 4 | EARTHING STATION : | | | | |
| (i) | Earthing installation as per I.E. rule conforming | Set | 2 | | |
| | Supply, Installation, Testing and Commissioning of Maintenance Free | | | | |
| | Earthing system made up of copperbonded rod of 10 feet length,23 | | | | |
| | mm dia. (Minimum copper bonding shall be 0.25mm) along with Rod- | | | | |
| | toConductor connectors, Earth enhancement material, Pit Cover and | | | | |
| | other accessories as required and as per specification and other | | | | |
| | applicable codes (include chamber for earthing, Earthing certificate to | | | | |
| | be submitted along with the bill). | | | | |
| | | | | | |
| (ii) | Supply laying 2x8SWG copper bear wire from earth spike to main | | | | |
| | panal (Electrolite wire) | Mts | 20 | | |
| 5 | MAIN ELECTRICAL DISTRIBUTION | | | | |
| | Main Panel (wall Mounted Type) | | | | |
| | Supply & erection of 6way Electric panel made of 16 gauge M.S sheet with double coated painting consisting 3No (4x40)mm copper strips of suitable length for 200 Amp current rating with supply & erection of followings 1) 63Amp TPN switch 1No make HPI/Havells/standard with HRC fuses II) 63 Amp D.P change over switch 1No III)63A Rotary switch -1No IV)10 Amp SP MCB-6No v)Three phase indicator & All internal wiring in D.B Should be 10Sq mm wire. | Set | 1 | | |
| | POWER DB & AC DB. Make standard/Legrand/ABB ,Double door | | | | |
| | 6 way TPN MCB DB with TP MCB as incoming | | | | |
| | 63 TP&N MCB as main | | | | |
| | 16Amps SP MCB - 8 Nos (Ac :3 Nos + 2X6amp : 4Nos and 1Nos spare) +32AMPS SP X10 NOS. (Ac 3 Nos+15 Amp: 6 Nos, 1No Spare) | | | | |
| 5.3 | including Neutral Bar. 01 Set | Set | 1 | | |
| | | | | | |

| | | | | | |
|------------|---|------|----------|--|--|
| | LIGHTING DB Make standard/Legrand/ABB | | | | |
| | 6 way TPN MCB DB with TP MCB as incoming | | | | |
| | 63A TP&N MCB as main | | | | |
| | 32 AMP DB MCB 1No: For Strong room) | | | | |
| | 16 Amps SP MCB - 03 Nos.+ (BM +Toilet) each 1No + 1No spare | | | | |
| | 12 Amps SP MCB - 12 Nos. (Hall - 4Nos + Store room 1 No +Exteranl Lighting 1No.:+ Ups 1No + wall Fan 3 Nos.2 No spare) | | | | |
| 5.4 | Including Neutral Bar. 01 Set | Set | 1 | | |
| 6 | UPS SYSTEM (Branch) | | | | |
| 6.1 | UPS Main DB Supply, erection, testing and commissioning of three phase 4 WAY, TPN MCB DB double door type with "C" Curve MCBs, IP 42 powder coated for UPS with 63A 4P MCBs - 1No as INCOMER 32A TP MCBs - 3 Nos. as OUTGOING (UPS :2Nos and 1 set ;: Spare Including all interconnections & accessories etc Make standard/Legrand/ABB | Nos | 1 | | |
| 6.2 | Supply & Fixing of 32A DP MCB in 2way SPN Db IP 20 metallic directly on wall Raw power Incoming & OutGoing supply for UPS (Branch :2 Nos & ATM 1No.) | Nos | 2 | | |
| 6.3 | UPS DB-1 & 2 combined 12 Way SPN MCB DB with 'C" curve MCBs. Incoming : 2 No. 40A DP MCB Outgoing : 8 Nos 6/10A (BM: 1+1 Nos with lighting : Server & Data Rack (1+1) Nos:C.C 2Nos with lighting :counter :2 Nos) SPO MCBs Make standard/Legrand/ABB . Repective UPS lighting to be connected.(BM,C.C,Banking hall 2Nos) or as per SLD | Nos | 1 | | |
| 6.4 | Supply and installation of modular type 3 nos 6A multi pin sockets with 2 nos 6A one way switch with indicator housed in MS box to be fixed in partitions or concealed in wall. The box shall be painted with 2 coats of enamel paint over a coat of red oxide primer including making connections complete the rate inclusive of Supplying and running of 3 runs of 2.5 sq.mm UPS DB's to individual powerstation through .(looping 2 sets of 3X6 A socket outlet in one circuit / or as per SLD the following size of 660 volts grade, Finolex brand PVC insulated wire (For UPS point only).(For B.M,C.C,Sever each 2Nos.) +3 Nos for Counter+Rack 1Nos) | Nos | 7 | | |
| 6.8 | Supply and Installation of Moduler type 2 X 20A plug & socket housed in for UPS output control (Branch 2 Nos & ATM 1No.) | Nos | 2 | | |
| 6.9 | Supply & Laying of 2 runs of 4.0 Sqmm and 1 run of 2.5 sqmm, PVC insulated, single core, multistranded copper conductor cable in suitable rigid / flexible metal conduitfrom 3 KVA UPS to UPS DB | mtr | 10 | | |
| | | | | | |
| | sub total I | | | | |
| 8 | ELECTRICAL FITTINGS (S/I/T/C | | | | |
| 8.4 | TUBELIGHT - NEW LED TUBELIGHT 20 watt PHILIPS/WIPRO MAKE. | Nos | 22 | | |
| 8.5 | HANGING LIGHT - LHECDOL5PW1W040 (40WATTS), PHILIPS/WIPRO MAKE | NOS. | 3 | | |
| 8.6 | 150 mm dia Heavy Duty Exhust fan 230 voltA.C.(Havells / Crompton make).(UPS & Toilet) | Nos | 3 | | |
| 8.7 | Metal body Wall mountaing fan 450 mm dia 230 volt A.C. PHILIPS/WIPRO MAKE | Nos. | 1 | | |
| 8.8 | Supply of Ceiling fan with 1200mm sweep, double ball bearing motor, capacitor, three MS blades die cast Al housing in stove enameled white with, suspension rod including all accessories of approved make.(5 star rated) (ORIENT/KHAITAN).(UPS,Strong room & Store room) | Nos. | 9 | | |
| | | | | | |
| | SUB TOTAL | | | | |
| | | | | | |
| | TOTAL FOR ELECTRICAL WORK (B) | | | | |
| | * GST EXTRA AS APPLICABLE | | | | |